

Mixer Amplifier with USB/SD/FM/Blue Tooth EA-60A/EA-120A/EA-240A/EA-350A/EA-500A



Features:

- Compact mini size public address amplifier
- Tabletop mixer amplifier with Mp3 player, FM radio & blue tooth
- Rate power output at 60W, 120W, 240W, 350W to 500W
- Speaker output of 100V or 70V & 4 Ohm-8 Ohm-16 Ohm
- Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and blue tooth
- LED indicators for power, clip, protect and signal
- Mic1 of balanced XLR input with dipswitch of phantom power on/off & highest VOX priority on/off
- Mic/line2-3 switchable inputs unbalanced 6.3mm jack
- Line 1-2 input of RCA input and one RCA line output
- Volume control for Mic1-3, line1-2, bass/treble and master
- Complete amplifier protection includes short-circuit, clip, overload and high temp
- AC230V power supply system

Specification:

Model	EA-60A	EA-120A	EA-240A	EA-350A	EA-500A
Description	Mixer Amplifier with USB/SD/FM/Blue Tooth				
Rated Power Output	60W	120W	240W	350W	500W
Speaker Outputs	100V or 70V & 4 Ohm-8 Ohm-16 Ohm				
Connector	Mic1 input by balanced XLR with phantom power & VOX highest priority Mic/line switchable input 2-3 unbalanced 6.3mm jack Line1-2 inputs by RCA; Line output by RCA				
Input	MIC1-3: 5-8mV, 600 Ω ; Line, 150-470mV, 10K Ω , unbalanced RCA				
Line Out	0.775(0dBV)				
Frequency Response	60Hz-15kHz(\pm 3dB)				
S/N Ratio	Line \geq 85dB, Mic \geq 72dB				
THD	Less than 0.5%				
Protection	Short-circuit, clip, overload and high temp protection				
Power Consumption	80W	150W	310W	450W	650W
Power Supply	AC230V; 50-60Hz				
Dimension	484x405x88mm				
Weight	7.0kg	7.1kg	8.6kg	8.7kg	8.9kg

Rear Panel:

