

The MM-700F is a 6-input and 4-zone-output pre-amplifier with easy control of mixer functions and digital processing. Both music selection and volume control can easily controlled via remote control. Matrix and DSP settings are made simply without a computer – reducing time spent on installation and system tuning.



Article number:MM-700F-EB 1CE  
Alternative products: MA-725F-EB

## Specifications

Power source	100 - 240 V AC, 50 / 60 Hz
Frequency response	20 Hz - 20 kHz (-3 dB / +1 dB, LPF OFF)
Distortion	< 1 % (at 1 kHz, rated input/output)
Power consumption	9 W (rated output)
S/N ratio	Mic: 60 dBV or more, Line: 75 dBV or more (A-weighted)
Inputs	Priority 1-2: Mic -60 dB/Line -10 dBV selectable, 2.2 kΩ, electronically-balanced, removable terminal block Line In 1-4: -10 dBV, 10 kΩ, unbalanced, 2 RCA jacks (Stereo summing)
Outputs	Line Out 1-4: 0 dBV, 600 Ω, unbalanced, RCA jack MOH: 0 dBV, 600 Ω, transformer balanced, removable terminal block
Controls	Power: ON/OFF switch, Power remote terminal Priority 1-2: MIC/LINE selector switch, Gain control, Assign switch, Auto mute switch, Mute sense control, Manual mute terminal, Mute hold time control, Priority mix switch LINE IN 1-4: Gain control, Assign restriction switch Output 1-4: LINE IN 1-4 selector switch, 4 x Line Output, HPF switch, DSP bank selector switch, DSP preset selector switch Remote 1-4: Remote control connector (RJ-45), Remote link switch
Signal processing	64 DSP presets at each output channel, selectable
PC software	Browser based remote control
Dimensions (W x H x D)	420 x 107,6 x 350 mm
Dimensions (ø x D)	x 350 mm
Finish	Aluminium, hairline, black,



**MM-700F**

---

Appearance